

Wiper Motor

Connect the wiper motor plug as follows: -



1 2 3 4 5

Connect Blue/Green wire to terminal 1 of the wiper motor (see above)

Connect Pale green/Red wire to terminal 2 of the wiper motor.

Connect Green/Brown wire to terminal 4 of the wiper motor.

Connect Green wire to terminal 5 of the wiper motor.

Connect Black wire to wiper motor body using a ring connector to one of the motor cover screws.

Terminal 3 is not used.

Instrument Wiring

This chart shows the instrument cluster connections. Read this in conjunction with the attached section on tachometer wiring and the original wiring chart.

Where changes have been made from the original wiring chart, these are highlighted with the word **NEW** next to them.

The diodes supplied are no longer needed.

Pin number	Status	Connect to
1		Red
2		Blue/White
3		Black
4		Not used
5	NEW	Black/Yellow X 2
6		Blue/Green from engine multiplug
7		Green/Black
8		Black
9		Not used
10		Not used
11		Not used
12		Green
13	NEW	Green/White
14	NEW	Green/Red
15		Not used
16		Not used
17		Not used
18	NEW	Not used
19		Brown/Yellow on engine multiplug
20	NEW	White/Black on engine multiplug
21	NEW	Connect to Earth
22		White/Brown on engine multiplug
23		Not used
24	NEW	To positive side of coil

Also to Negative Coil